# **Bourdon Tube Safety Pressure Gauge**

With direct limit switch contact assembly (type M) Safety category S3 according to DIN EN 837-1





This data sheet contains information on the maximum possible number of contacts, on electrical connections, options and ordering information concerning the Bourdon tube pressure gauge models RSCh 63 with limit switch contact assemblies with 1 or 2 magnetic contacts, as well as dimensional drawings with the position of the electrical connections.

Data sheet 1610 contains all details concerning the available versions of model RSCh without limit switches. These details as well as the required ordering information apply also to the version with limit switches, unless otherwise stated below. A version with case filling is not available.

Model overview 9.1000 contains general and detailed definitions, applications and operating principles for the respective limit switch types. It also provides detailed information on the selection, switching functions and minimum spans, on operating conditions, explosion protection, options and others.



**Available Limit Switch Contact Assembly** 

Direct (electromechanical) Magnetic contact M

**Maximum Possible Number of Contacts** Up to 2 x M

Degree of Protection (DIN EN 60 529 / IEC 529) IP54

#### **Blow-out Device**

Blow-out back; when pressure increases in the case, the entire case back separates, allowing full relief

#### **Nominal Case Size**

63 mm (21/2")

#### Window

Polycarbonate

#### Safety Category According to DIN EN 837-1

S3, safety pressure gauge with break-proof solid front and blow-out back

pressure ranges up to 1000 bar (15,000 psi) (type - 3) up to 600 bar (10,000 psi) (type - 1)

marking (S), see also sectional drawing on page 2

#### **Adjusting Mechanism Limit Setting Pointer**

All instruments are equipped with an adjusting lock in the window. With the removable key, the limit setting pointer can be externally set to the value of the desired switch point.

#### **Electrical Connection**

On the lower right side of the case 1 m connection cable Screwed cable gland M12x1.5

For the position of the electrical connection, please refer to the dimensional drawings on page 2.



#### **Options**

- Adjusting lock with non-removable key
- Window laminated glass without adjusting lock, adjustment after removal of the bayonet ring - please regard the safety instructions in our operating instruction B5, paragraph 6.4 "Adjusting the Limit Setting Pointers"
- Switching distance fixing for 2 contacts upon request
- Connection cable longer than 1 m upom request
- Plug connector according to DIN EN 175 301-803 construction types A and C, on the left side at 9 o'clock (dimensional drawings upon request), see also page 2
- Other position of the electrical connection upon request

## **Ordering Information**

When installing limit switches, the order text of the basic device (see data sheet 1610) is supplemented by

Code letter Code number for the switching function (clockwise direction of action)

magnetic contact

making contact breaking contact

single change-over contact 1st and 2nd making contact 11

1st making contact / 12

2<sup>nd</sup> breaking contact 1st breaking contact / 2<sup>nd</sup> making contact

1st and 2nd breaking contact

RSCh 63 - 3, 0 - 10 bar, G 1/4 B, M21 **Example:** 

#### **Please Note**

For an optimal function of the devices with limit switch, please specify in your order text:

- · correct specification of the switching function
- · switching pressures
- switching ranges, which are beyond the adjustment ranges defined by us
- · if a counterclockwise switching direction is required

www.armano-messtechnik.com



# Case Configurations, Code Letters, Dimensional Data and Weight, Options


Compared to the basic models, there are deviations in the front-to-back sizes, see table. Please refer to data sheet 1610 for the other dimensional data.


#### **Bottom Connection**

#### **Lower Back Connection**

#### without mounting device


without code letters









code letter: r






### with back flange for surface mounting

code letters: Rh







Version Rh including 3 separate mounting spacers.

# with front flange for panel mounting

code letters: Fr







Versions Fr and rFr are supplied with a removable front flange and 3 mounting brackets welded to the case.

Dimensional Data (mm/inch) and Weight (kg/lb)					
NCS	b / b1	b2	g <sup>±1</sup> / g1 <sup>±1</sup>	r6	approx. weight1)
63 <b>2</b> ½"	80 <b>3.15</b>	100 <b>3.94</b>	102 <b>4.02</b>	45 <b>1.77</b>	0.30 <b>0.66</b>

#### **Options**

#### Plug connector DIN EN 17 5301-803

• IP65, 3-pin + PE and protective contact

Construction type A	Construction type C		

1) the data are based on the version with bottom connection and limit switches with 2 contacts